

LED Strip 12W CCT RGBW 3M Smart



Features

() Multicolor

Bluetooth Connection





Voice Control











Follow the steps below to set up your strip light via the Smart Life app.

Step 1. Download Smart Life App

Go to Google Play or the App Store or scan the the QR code below to download and install the Smart Life app.





Step 2. Log In to Smart Life App

Open the app and use your account to log in. If you don't have a Smart Life account, tap Sign Up and the app will guide you through the rest.



Step 3. Connect Hardware

Connect all the parts, When connecting the strip light to the controler.



Button Explanations

 Press once to enter into scene mode Press twice to turn off your strip light Press and hold for 5s, then release to restore factory settings

Add Your Devices (Method 1: Default Mode) Step 1. Discover Devices

Make sure your phone is connected to Wi-Fi & Bluetooth. Tap the • button in the app and follow app instructions to complete the setup



Step 2. Power Up Strip Light Step 3. Devices being added

Plug in the power adapter and wait until the Strip Light Select the device which you will add. blinks blue. The prompt page will automatically appear in Step 4. Setup Complete

the app. Press Add. Note: Do not roll up when using, Spread out the Strip Light before connect the power supply.

Add Device

Add Manually

V V V

Plog Social Social (NCAN-F) (N-F) (Option

V V

Harris (600) (2-49-6569-1) NO-

Discovering devices...



Now you can start using your Strip Light.

Install Your Smart Strip Light After you have set up the Strip Light via the Smart Life app,

you can cut it to length-fit and attach it to any surface with the adhesive. To avoid damaging your Strip Light, please note the following Installation Tips before installing





Cut Only On Specific Areas of Strip Light

You can custom tailor the length of your Strip Light with scissors. Unplug the Strip Light and cut only on these specific areas or your Strip Light will no longer function.

Avoid Sharp Turns

Carefully roll the Strip Light into a clover or use a gentle hill when making 90° turns like those need behind a TV. Sharp bends can damage your Strip Light.

Avoid Bending on LED Beads

The bend should be avoided just in the position of the LED components, so as not to damage the product and affect the life of the product.

Use gentle weeps when bending Strip Light around corners and avoid creases as they may cause damage.

Avoid Sharp Corners

static and stays away from water

Step 1. Choose Location

Step 2. Remove Adhesive Tape

Unplug the Strip Light first. Peel away the adhesive backing bit by bit and stick your Strip Light to the surface.



Stick the Strip Light and press over it about 10-15 seconds. Secure the controller with the adhesive pads. Do not move it to other place after



After you successfully set up your Strip Light, you will see the Devices page on the Smart Life app. You can add

Choose a dry, clean, and smooth surface. Wipe off the dust. Otherwise, the Strip Light will be easily fall off. Note: Choose a location that avoids

Device Page On the Device page, you can instantly turn on/off the

Strip Light.



Main Device Control

On the Devices page, tap a Strip Light and you can adjust the light brightness or color, set schedules, save a shortcut new devices, control multiple devices simultaneously in for a light effect, and configure the Strip Light settings. a group, configure account settings, and more.

Configure Your Smart Strip Light

Adjust Color

Choose a preferred color for your Strip Light.



Choose a preferred scene mode for your Strip Light. Press Edit to custom scene mode.



Sync with Music Tap Music to match color changes with the beat of

the music playing on your speakers. You can enjoy the "dancing" through your mobile microphone.



Tap"#" and select Timer you can customize a countdown time to turn the light on or off automatically.





Tap "#" and select Schedule to simplify your daily routine by creating automatic On/Off actions. (You need connect a Bluetooth mesh Gateway to use this function)



Add Schedules

Smart Strip Light

Configure Device Setting

information.

Tap "∠" to configure device settings and check device A scene is a preset group of smart devices that can be customized and activated simultaneously at the touch of a button from your smartphone or tablet, allowing you to easily set your mood, activity or fit any special occasion.

Create Scenes

1. On the Scenes page, tap +.



Press and hold the light switch controller for 5 seconds

On the Home page on Smart Life app, tap "...." the Strip or more then release. The Strip Light blinking reb after that indicates a successfully factory reset.

On the Device page on Smart Life app, touch and hold the device name, then select the device you want to delete and tap Remove Device.



Light and tap > Device Management.

Factory Reset



Works with Alexa and Google Home

Use the Smart Life app to pair your Strip Light with Amazon Alexa, Google Home Assistant, and other third-party services to enjoy a full hands-free experience. (You need connect a Bluetooth mesh Gateway to use this function)

